



Quick Installation Guide

Step 1 - Connect the cables to IP device

Step 2 - Set up network environment

The default IP address of your device is 192.168.0.100. Please make sure that the device and your PC are on the same network segment before running the installation. If the network segment was different between you PC and the device, change your PC's settings as below:

IP Address: 192.168.0.XXX
Subnet Mask: 255.255.0.0

Step 3 – View video on web page

- Open web browser and enter the IP address of the device (<http://192.168.0.100>)
- Enter the default user name (root) and password (pass)
- Turn-off 'pop-up blocker ' and install the Active X driver
- Click the PLAY button to start viewing

Step 4 – Setting IP Address from web browser

- Click SETUP on upper right corner of the web page.
- Click NETWORK
- Click GENERAL
- Change the IP Address settings and click SAVE

**To learn how to set up the web page for advanced configuration, refer to the Web Page User's Manual on your FROG ENCODER TOOLS DISK*

Advanced Set-up using IPAdminTool

Step 1 – Run the IPAdminTool program



(FROG ENCODER TOOLS DISK: IPAdminTool V2.4.3/IPAdmin Tool)

- Highlight the encoder device
- Click IP SETUP
- Make IP Address changes
- Click SETUP

**You may get a GATEWAY error. Set the GATEWAY to either the known gateway or XXX.XXX.XXX.254 or 1*

-Click OK to restart the device. It will take approximately 120 seconds to restart the device

-Click REFRESH to make sure that the new IP Address change has been saved

**To learn how to use the advanced features of the IPAdminToolweb page for advanced configuration, refer to the IPAdminTool User's Manual on your FROG ENCODER TOOLS DISK*

Milestone/OnSSI Deployments Known Issues

Select Device Driver Video0230

Please contact Tech/Rep Support for specific installation instructions if you have any problems or need to use higher device packs

Advanced Technical Support

Technology Representatives Inc.
21 Park Street, Suite 307, MS 16
Attleboro, MA 02703
support@techrepvideo.com

Phone: 508-809-6316
Fax: 508-809-6319
Cell/Text: 508-326-6000

